Accessories

Electrical accessories



First and second opening release - YO

Size	Type	Code
E1.2..E6.2	YO_E1.2..E6.2 24V AC/DC	1SDA073668R1
E1.2..E6.2	YO_E1.2..E6.2 30V AC/DC	1SDA073669R1
E1.2..E6.2	YO_E1.2..E6.2 48V AC/DC	1SDA073670R1
E1.2..E6.2	YO_E1.2..E6.2 60V AC/DC	1SDA073671R1
E1.2..E6.2	YO_E1.2..E6.2 110-120V AC/DC	1SDA073672R1
E1.2..E6.2	YO_E1.2..E6.2 120-127V AC/DC	1SDA073673R1
E1.2..E6.2	YO_E1.2..E6.2 220-240V AC/DC	1SDA073674R1
E1.2..E6.2	YO_E1.2..E6.2 240-250V AC/DC	1SDA073675R1
E1.2..E6.2	YO_E1.2..E6.2 380-400V AC	1SDA073677R1
E1.2..E6.2	YO_E1.2..E6.2 415-440V AC	1SDA073678R1
E1.2..E6.2	YO_E1.2..E6.2 480-500V AC	1SDA073679R1

First and second closing release- YC

Size	Type	Code
E1.2..E6.2	YC_E1.2..E6.2 24V AC/DC	1SDA073681R1
E1.2..E6.2	YC_E1.2..E6.2 30V AC/DC	1SDA073682R1
E1.2..E6.2	YC_E1.2..E6.2 48V AC/DC	1SDA073683R1
E1.2..E6.2	YC_E1.2..E6.2 60V AC/DC	1SDA073684R1
E1.2..E6.2	YC_E1.2..E6.2 110-120V AC/DC	1SDA073685R1
E1.2..E6.2	YC_E1.2..E6.2 120-127V AC/DC	1SDA073686R1
E1.2..E6.2	YC_E1.2..E6.2 220-240V AC/DC	1SDA073687R1
E1.2..E6.2	YC_E1.2..E6.2 240-250V AC/DC	1SDA073688R1
E1.2..E6.2	YC_E1.2..E6.2 380-400V AC	1SDA073690R1
E1.2..E6.2	YC_E1.2..E6.2 415-440V AC	1SDA073691R1
E1.2..E6.2	YC_E1.2..E6.2 480-500V AC	1SDA073692R1

YO/YC test unit

Size	Type	Code
E1.2...E6.2*	YO/YC test unit_E1.2...E6.2	1SDA082751R1

*Only as loose part

Undervoltage release - YU

Size	Type	Code
E1.2..E6.2	YU E1.2..E6.2 24V AC/DC	1SDA073694R1
E1.2..E6.2	YU E1.2..E6.2 30V AC/DC	1SDA073695R1
E1.2..E6.2	YU E1.2..E6.2 48V AC/DC	1SDA073696R1
E1.2..E6.2	YU E1.2..E6.2 60V AC/DC	1SDA073697R1
E1.2..E6.2	YU E1.2..E6.2 110-120V AC/DC	1SDA073698R1
E1.2..E6.2	YU E1.2..E6.2 120-127V AC/DC	1SDA073699R1
E1.2..E6.2	YU E1.2..E6.2 220-240V AC/DC	1SDA073700R1
E1.2..E6.2	YU E1.2..E6.2 240-250V AC/DC	1SDA073701R1
E1.2..E6.2	YU E1.2..E6.2 380-400V AC	1SDA073703R1
E1.2..E6.2	YU E1.2..E6.2 415-440V AC	1SDA073704R1
E1.2..E6.2	YU E1.2..E6.2 480-500V AC	1SDA073705R1

Accessories for circuit breakers

Control

Opening and closing release- YO/YC (Fig. 06)
The opening and closing releases enable the circuit breaker to be controlled remotely. Opening is always possible, while closing is available only when the closing springs of the operating mechanism are loaded and the circuit breakers is ready to close. The releases operate by means of minimum impulse current duration time of 100 ms.
Furthermore, they can operate in permanent service. In this case, if opening command is given by means of the opening release, the circuit breaker can be closed by de-energizing the opening release and, after a time of at least 30 ms, by controlling the closing.
The circuit breaker operating mechanism has an anti-pumping function that ensures safety and reliability.

—
Electrical diagram reference: figures 75, 77



—
Fig. 06

Second opening and closing release - YO2/YC2
For certain installations the redundancy of mechanisms and circuit breaker operating circuits is often requested. To answer these needs, the SACE Emax 2 circuit breakers can be equipped with double opening release and double closing release. The technical characteristics of the second opening release remain the same as those of the first opening and closing release. A double closing release can be used for E2.2, E4.2 and E6.2 circuit breakers; a second open release in an alternative to undervoltage release.

—
Electrical diagram reference: figures 72, 79

General characteristics			
Power supply (Un)		**AC**	**DC**
	24V	●	●
	30V	●	●
	48V	●	●
	60V	●	●
	110V...120V	●	●
	120V...127V	●	●
	220V...240V	●	●
	240V...250V	●	●
	380V...400V	●	-
	415V...440V	●	-
	480V...500V	●	-
Operating limits (IEC60947-2 standards)		YO/YO2: 70%...110% Un YC/YC2: 85%...110% Un	
Inrush power (Ps)		300VA	300W
Continuous power (Pc)		3.5VA	3.5W
Opening time (YO/YO2)			
	E1.2	35 ms	
	E2.2 ... E6.2	35 ms	
Closing time (YC/YC2)			
	E1.2	50 ms	
	E2.2 ... E6.2	70 ms	