SNAP-AIMA-I

01 / Product identity and electrical data

Opto 22 SNAP-AIMA-I is a two-channel isolated analog current input module for a compatible SNAP PAC I/O rack. Its channels independently measure bipolar current signals; the installed rack and I/O processor complete the acquisition system.

Input channels	2, isolated from one another	**Input type**	Analog current
Input range	−20 to +20 mA	**Maximum overrange**	±10%
Resolution	0.8 µA	**Accuracy**	0.05% (10 µA)
Data freshness	11 ms	**Input response**	99.9% / 19.9 µA / 10 ms
Channel isolation	250 V continuous; 1500 V transient	**Optical isolation**	4000 V
Transformer isolation	1500 V	**Input resistance**	200 Ω per channel
Maximum survivable input	36 mA or 9 VDC	**Rack power**	5 VDC (±0.15 V) at 200 mA
Operating temperature	−20 to +70 °C	**Field wire size**	22 to 14 AWG
Loop excitation	External; this model does not source current		

Source boundary

The electrical figures are from the exact SNAP-AIMA-i section of Opto 22 Form 1182-240326. Mounting and system statements use the same manufacturer document; do not transfer loop-sourcing features of the distinct iSRC model.

SNAP-AIMA-I

02 / Application and compatibility

Separate field references

Acquire two grounded instruments without tying their signal references together at the module input.

Bipolar signal capture

Use the documented −20 to +20 mA measurement span where an application requires signed current values.

SNAP PAC integration

Place the module on a compatible rack and map both channels through the installed I/O processor and control strategy.

Maintenance replacement

Retain each channel’s source, polarity and scaling while exchanging an exact-model input module.

Field precautions

Isolate the field circuits

Remove rack and loop power under the site isolation procedure before wiring the pluggable connector.

Supply the transmitter separately

SNAP-AIMA-I does not source excitation; verify the external loop supply and return path before diagnosing a zero reading.

Observe input limits

Keep normal current within the selected range and avoid exceeding the stated 36 mA or 9 VDC survivability limit.

Preserve isolation

Do not bridge the two channel returns or defeat the designed field grounding solely to simplify wiring.

SNAP-AIMA-I

03 / Technical decisions and support

Why might SNAP-AIMA-I show zero for a healthy two-wire transmitter?

The module does not furnish loop excitation. Check the external supply, loop continuity, polarity and transmitter demand, then read the channel value and fault state through the rack processor.

What test points help verify SNAP-AIMA-I scaling?

Use a calibrated current source at representative negative, zero and positive values within −20 to +20 mA. Compare raw channel values and engineering units in the controller strategy and record as-left results.

How should the two SNAP-AIMA-I channels be grounded?

Treat the channels as separately isolated measurement paths. Follow each instrument loop drawing and rack grounding design; do not add a common bridge between channel returns simply because the signals share one module.

What rack conditions should be checked before fitting SNAP-AIMA-I?

Confirm the rack and I/O processor are compatible and the 5 V supply budget includes 200 mA for this module. Align the keyed connector and secure the retention hardware without forcing the pins.

Can SNAP-AIMA-I be exchanged for the SNAP-AIMA-iSRC sourcing model without a wiring review?

No. The iSRC has a separate 24 V loop-source arrangement, whereas SNAP-AIMA-I measures current only. Verify the field supply and connector wiring before selecting a replacement variant.

How can a noisy SNAP-AIMA-I reading be traced?

Compare both channels separately, inspect shield routing and field grounding, and inject a stable current at the terminal connector. The isolated inputs reduce ground-loop coupling but do not correct an unstable source or bad wiring.

Technical basis: Opto 22 SNAP Isolated Analog Input Modules, Form 1182-240326, pp. 1 and 4.

Technical enquiry

sales13@apterpower.com | +86 18030235313