Allen-Bradley 845H-SJDZ24FWY2C

COMPLETE PRODUCT INFORMATION / technical and application dashboard

Allen-Bradley 845H-SJDZ24FWY2C is a size 25 optical incremental encoder with a square-flange mount, 3/8 in. shaft, 1024 pulses per revolution, 8–24 V DC supply and 5 V RS-422 differential line-driver outputs.

01 Product identity and operating role

Complete identity
845H-SJDZ24FWY2C

Product function
Size 25 Incremental Optical Encoder

Supply scope
Offer the 845H-SJDZ24FWY2C encoder with its selected mating-connector option; coupling, counter and application cable must be verified separately.

System family
Bulletin 845H Size 25

Engineering priorities

Counter configuration
Use 1024 PPR and the selected x1/x2/x4 decoding mode to establish counts per revolution.

Signal pairing
Land A/$\overline{A}$, B/$\overline{B}$ and Z/$\overline{Z}$ as differential pairs; preserve the correct 5 V receiver interface.

Mechanical alignment
Use a suitable coupling and verify flange and shaft alignment before applying speed.

System context

The complete 845H-SJDZ24FWY2C order code selects a square-flange size 25 encoder with a smooth 3/8 in. shaft and 1024 pulses per revolution. The FW code describes the incremental code disk; the A/B channel interpretation depends on the counter decoding mode, so pulses per revolution must not be confused with counted edges.

The encoder is supplied from 8–24 V DC but its selected output option is a 5 V differential RS-422 line driver. The 10-pin radial connector carries A/$\overline{A}$, B/$\overline{B}$ and zero-index Z/$\overline{Z}$ paths along with supply, return and case grounding. The C suffix identifies the mating connector option; inspect the offered connector and cable before replacing the installed unit.

Rockwell specifies a maximum 210 kHz data response and 6000 rpm mechanical ceiling for this family. At 1024 PPR, the mechanical ceiling is the binding speed limit under the stated response values. Fit a suitable flexible coupling, preserve shield and grounding arrangements and prove direction, index and counted speed against a known reference during commissioning.

Counter field identification

Data channels	A/A-bar and B/B-bar provide the differential quadrature signals to the matched receiver.
Index channel	Z/Z-bar is the once-per-turn marker; capture depends on the installed counter configuration.
Power boundary	The 8–24 V DC encoder supply and 5 V RS-422 output are distinct code options; do not connect the receiver to the supply pins.

02 Technical capability map

Order-code values come from the Bulletin 845H selection guide; frequency, environmental and mechanical limits are 845H family specifications.

Encoder family	Bulletin 845H, size 25 high performance
Code format	Incremental A/B quadrature plus zero index
Mounting option D	Square flange
Shaft option Z	Smooth 3/8 in. diameter
Supply option 2	8–24 V DC, unregulated
Output option 4	5 V DC differential line driver, RS-422
Resolution option FW	1024 pulses per revolution
Connection option Y2	Radial side connector
Connection suffix C	Mating connector included

Encoder connector	10-pin for differential line-driver output
A/B phase relation	90° ±22° electrical; A leads B counterclockwise, family data
Zero-index pulse	Half cycle gated to channel B, family data
Maximum data response	210 kHz, family data
Maximum index response	125 kHz, family data
Mechanical speed ceiling	6000 rpm, family data
Enclosure protection	NEMA Type 4 and 13; IP66, family data
Operating temperature	0 to +60 °C, family data
Storage temperature	−25 to +90 °C, family data

03 Integration and use

Rotary speed feedback

Convert shaft rotation into A/B pulse trains for the installed drive or counter input.

Position accumulation

Use counter edges and the configured decoding factor to track relative angular travel.

Direction determination

Compare the A/B phase relationship against the configured machine convention.

Reference indexing

Use the gated Z pulse for a once-per-revolution reference where the machine sequence requires it.

Technical decisions

Supply versus output	Code 2 accepts 8–24 V DC supply; code 4 drives a separate 5 V differential RS-422 receiver.
Counts per revolution	FW denotes 1024 PPR; x1/x2/x4 counter decoding produces 1024/2048/4096 counted edges per turn.
Direction convention	The family reference defines A leading B for counterclockwise shaft rotation; verify the installed controller convention.

Index qualification	The Z pulse is gated to channel B; establish the machine home reference with the installed counter logic.
Speed boundary	At 6000 rpm and 1024 PPR the A-channel pulse frequency is 102.4 kHz, below the family 210 kHz data-response limit.
Connector scope	Y2 is the radial side connection; C identifies a mating connector option, not a supplied application cable.
Cable pair discipline	Carry each complementary A, B and Z signal as a pair and follow the specified ground and shield arrangement.
Mechanical fit	Confirm square flange, smooth 3/8 in. shaft, coupling geometry and permitted shaft loading at the machine.
Acceptance evidence	Record the complete marking, known-turn count, direction, index capture and operating speed.

04 Installation and diagnostic review

Power-output distinction
Check 8–24 V encoder supply and 5 V RS-422 receiver compatibility as separate requirements.

Connector identity
Verify the radial 10-pin interface and supplied mating connector against the installed cable.

Shaft coupling
Avoid rigid shaft coupling; inspect offset, axial load and flange alignment.

Pulse scaling
Set 1024 PPR and the actual x1/x2/x4 counter mode before validating displayed speed.

Shield routing
Keep paired signal conductors and the approved shield bond away from high-noise power wiring.

Acceptance test
Rotate in a controlled direction and prove A/B order, zero index and speed at the controller.

Technical FAQ

How should 845H-SJDZ24FWY2C counts per revolution be configured in a quadrature counter?	Start with 1024 pulses per revolution from the FW order code. A counter using x1, x2 or x4 decoding may accumulate 1024, 2048 or 4096 edges per shaft turn; select the mode used by the installed control program and prove it with one known revolution.
Why can 845H-SJDZ24FWY2C be powered correctly yet produce unusable counter signals?	The encoder supply is 8–24 V DC while code 4 delivers 5 V RS-422 differential outputs. Verify the receiver input type, A/$\overline{A}$ and B/$\overline{B}$ polarity, cable continuity and ground reference rather than assuming supply and signal voltage are identical.
How is direction reversal diagnosed on 845H-SJDZ24FWY2C?	Check the A/B phase order against a known shaft direction; the family reference states that A leads B for counterclockwise rotation. Compare wiring polarity and the controller direction convention before changing software scaling.
How should the index signal of 845H-SJDZ24FWY2C be proved?	Observe the differential Z/$\overline{Z}$ pair during a slow controlled turn and confirm one valid gated reference event per revolution. Compare the controller capture point with the machine home sequence and check the index receiver wiring.
What limits the usable shaft speed of 845H-SJDZ24FWY2C?	For this 1024-PPR selection, compare the family 210 kHz data response with the 6000 rpm mechanical ceiling. The 1024-PPR pulse frequency at 6000 rpm is 102.4 kHz, so the mechanical limit is lower under these stated conditions; also respect the coupling and shaft-load limits.

What connector inspection matters before replacing 845H-SJDZ24FWY2C?	Confirm the radial 10-pin differential connector, the C-suffix mating connector and the pin assignments in the applicable Rockwell drawing. Compare shell, keying, cable exit and strain relief with the installed harness before energizing.

05 Service and acceptance

Intermittent speed

Correlate counter dropout with shaft speed, coupling motion, shield bond and cable strain.

Noise-induced counts

Inspect complementary-pair routing, termination and separation from drive power cables.

Mechanical distress

Inspect flange alignment, coupling flexibility and shaft loads before replacement.

High-speed loss

Compare actual PPR-derived frequency with 210 kHz data response and 6000 rpm mechanical limit.

Wrong connector

Compare Y2 radial interface and C mating connector with the installed harness drawing.

As-left record

Retain measured supply, count per turn, rotation direction, index capture and final wiring record.

Lifecycle and supply boundary

The 845H family has been superseded by Rockwell Bulletin 847 incremental encoders. A lifecycle date or direct replacement for this exact complete catalog number has not been established here; review the installed interface and manufacturer migration guidance before substitution.

Evidence and applicability

Rockwell Automation C116 Sensor Catalog, Bulletin 845H selection guide and specifications. Order-code values come from the Bulletin 845H selection guide; frequency, environmental and mechanical limits are 845H family specifications.

Additional installation context: Rockwell Automation High-Speed Counter Module Installation Instructions, publication 1746-IN011C-EN-P.

Related model boundary

Other Bulletin 845H order codes may change the shaft, flange, supply, output, resolution or connector. Compare the full installed marking and manufacturer selection guide before considering a different encoder.

Discuss the complete marking with Apter Power.
sales13@apterpower.com | +86 18030235313