

EZ1081-07-00-010 + EZ1901-090

Eddy Current System

Emerson EZ1081-07-00-010 + EZ1901-090 combines an armored M10x1 EZ1081 sensor with a 1 m integral cable and an armored EZ1901 extension cable for a documented 10 m system length. The configured sensor provides a 2 mm eddy-current measuring range for compatible EZ1000 conversion electronics.

BRAND	Emerson	ORIGIN	USA
MODEL	EZ1081-07-00-010 + EZ1901-090	PRODUCT	Eddy Current System
FAMILY	AMS EZ1000 8 mm System	SOURCE	Emerson data sheet, December 2024; EZ1081 and EZ1901 ordering tables

MANUFACTURER SOURCE RECORD

AMS EZ1000 8 mm Sensor Data Sheet
Emerson data sheet, December 2024; EZ1081 and EZ1901 ordering tables

APTER POWER SALES TEAM

WHATSAPP / PHONE +86 180 3023 531
EMAIL sales13@apterpower.com
WEBSITE www.apterpower.com



EZ1081-07-00-010 + EZ1901-090

Product Overview

SYSTEM FUNCTION

Emerson EZ1081-07-00-010 + EZ1901-090 combines an armored M10x1 EZ1081 sensor with a 1 m integral cable and an armored EZ1901 extension cable for a documented 10 m system length. The configured sensor provides a 2 mm eddy-current measuring range for compatible EZ1000 conversion electronics.

FUNCTION 1

Forms a calibrated 10 m sensor cable chain

FUNCTION 2

Uses an armored M10x1 EZ1081 probe

FUNCTION 3

Provides a 2 mm measurement range

FUNCTION 4

Supports API or ISO scale-factor configuration

TECHNICAL NOTE

Keep the complete 10 m calibrated cable chain together and record the 70 mm case-length code before replacement. Verify the 0.5 mm initial air gap, target geometry and converter configuration before dynamic acceptance.

Technical Data and Acceptance

PARAMETER	VERIFIED VALUE
Complete configuration	EZ1081-07-00-010 + EZ1901-090
Sensor thread	M10x1
Sensor case length	70 mm
Integral cable	1 m, armored
Extension cable	9 m, armored
Total system length	10 m
Measuring range	2 mm
Initial air gap	0.5 mm
Scale factor	7.87 V/mm ±5% API or 8 V/mm ±5% ISO at 0–45 °C
Protection	IP67; IP68 with DOC-TEST

ENGINEERING BOUNDARY

Keep the complete 10 m calibrated cable chain together and record the 70 mm case-length code before replacement. Verify the 0.5 mm initial air gap, target geometry and converter configuration before dynamic acceptance.

Acceptance Path

1 IDENTITY

The exact probe and extension pair are recorded.

2 MECHANICAL

Thread, target and clearance are correct.

3 ELECTRICAL

Cable length and converter setup match.

4 FUNCTIONAL PROOF

Gap, polarity, response and alarm logic pass.

Applications and Engineering FAQ

APPLICATION	ENGINEERING CONTEXT
Shaft relative vibration	Measures non-contact shaft motion with a compatible converter.
Radial position monitoring	Tracks static position inside the documented linear range.
Key or speed reference	Detects a suitable metallic target when the converter is configured accordingly.
Exact cable-chain replacement	Restores the documented 1 m sensor plus 9 m extension arrangement.

Model-Specific FAQ - Part 1

QUESTION	ANSWER
What total cable length does Emerson EZ1081-07-00-010 + EZ1901-090 create?	The 1 m EZ1081 cable plus the 9 m EZ1901 extension gives the documented 10 m system length.
Which thread is used by Emerson EZ1081-07-00-010 + EZ1901-090?	The EZ1081 sensor code in this configuration uses an M10x1 mounting thread.
What case length is encoded in Emerson EZ1081-07-00-010 + EZ1901-090?	The sensor order code specifies a 70 mm case length.
What measuring range applies to Emerson EZ1081-07-00-010 + EZ1901-090?	The 8 mm EZ1000 sensor system has a 2 mm measuring range.

FAQ, Related Products and Source

QUESTION	ANSWER
Where should the initial gap be set for Emerson EZ1081-07-00-010 + EZ1901-090?	The data sheet states a 0.5 mm initial air gap.
Which scale factors are available for Emerson EZ1081-07-00-010 + EZ1901-090?	The official values are 7.87 V/mm ±5% for API scaling or 8 V/mm ±5% for ISO scaling at 0–45 °C.
Can the extension cable in Emerson EZ1081-07-00-010 + EZ1901-090 be omitted or exchanged casually?	No. The calibrated chain depends on the documented 10 m total length, so any extension change requires confirmation of the complete order and converter setup.
What is the final functional check for Emerson EZ1081-07-00-010 + EZ1901-090?	Verify connector integrity, converter selection, static gap, polarity, linear movement response and the configured alarm path with the full cable chain installed.

MANUFACTURER SOURCE RECORD

AMS EZ1000 8 mm Sensor Data Sheet
Emerson data sheet, December 2024; EZ1081 and EZ1901 ordering tables

Related Products on Apter Power

MODEL	APTER POWER PAGE
Bently Nevada 31000-0 0-00-00-000-00-00	View Bently Nevada 31000-00-00-00-000-00-00
Bently Nevada 31000-0 0-00-15-023-01-02	View Bently Nevada 31000-00-00-15-023-01-02
Bently Nevada 31000-0 0-00-15-035-01-02	View Bently Nevada 31000-00-00-15-035-01-02
Bently Nevada 31000-0 0-00-15-039-01-02	View Bently Nevada 31000-00-00-15-039-01-02
Bently Nevada 31000-0 0-00-15-047-01-02	View Bently Nevada 31000-00-00-15-047-01-02
Bently Nevada 31000-0 0-00-15-050-02-02	View Bently Nevada 31000-00-00-15-050-02-02
Bently Nevada 31000-0 0-00-15-051-01-02	View Bently Nevada 31000-00-00-15-051-01-02
Bently Nevada 31000-1 6-05-00-065-03-02	View Bently Nevada 31000-16-05-00-065-03-02

APTER POWER SALES TEAM

WHATSAPP / PHONE +86 180 3023 5313
EMAIL sales13@apterpower.com
WEBSITE www.apterpower.com



EZ1081-07-00-010 + EZ1901-090