4. I/O Module Sizes

IOTA Sizing is nominal (6in = 152mm, 9in =228mm, 12in =304mm, 18in = 457mm)I/O modules are associated with their respective IOTAs in the table below. An I/O Module is supported by one or more IOTAs.

I/O Module	IOTA	Description	Circuits	Size (in ")	Red.
CC-PAIH01		High-Level AI HART	16		√
	CC-TAIX01	AI IOTA		6	
	CC-TAIX11	AI IOTA Red		12	√
CC-PAIH02 CC-PAIX01 / 02		High-level AI HART High-level AI w/o HART	16		√
	CC-TAIX01	AI IOTA		6	
	CC-TAIX11	AI IOTA Red		12	√
	CC-TAID01	AI IOTA – 16 Channel Differential		9	
	CC-TAID11	AI IOTA Red – 16 Channel Differential		12	√
CC-PAIH51		High-level AI HART	16		√
	CC-TAIX51	AI IOTA		6	
	CC-TAIX61	AI IOTA Red		12	√
CC-PAIN01		High-level AI w/o HART	16		√
	CC-TAIN01	AI IOTA		6	
	CC-TAIN11	AI IOTA Red		12	√
CC-PPIX01		Pulse Input w/ Fast Cut-off	8		√
	CC-TPIX11	PI IOTA Red		12	√
CC-PAIM01		PMIO LL Mux	64		
	CC-TAIM01	PMIO LL Mux IOTA		6	
	FTA				
	Mx-TAMT04	LL Mux TC FTA	16	12	
	Mx-TAMT14	LL Mux TC FTA w/Remote CJR	16	12	
	Mx-TAMR04	LL Mux RTD FTA	16	12	
CC-PAIL51	CC-TAIL51	Low-level AI	16	9	
CC-PPIX01	CC-TPIX01	Pulse Input	8	12	√

5.3. Analog Input – CC-PAIX01 / 02

Function

The Analog Input Module accepts high level current or voltage inputs from transmitters and sensing devices.

Notable Features

- Extensive self-diagnostics
- Optional redundancy
- Supplies non-incendive field power
- Non-Incendive Power
- Fast loop scan

Detail Specifications –Analog Input

Parameter	Specification	
Input / Output Model	CC-PAIX02 - High-Level Analog Input	
IOTA Models	Non-Redundant	Redundant
	CC-TAIX01	CC-TAIX11
	CC-GAIX21	CC-GAIX11
	CC-TAID01	CC-TAID11
Input Type [1]	Voltage, current (2-wire or self-powered transmitters)	
Input Channels [1]	16 Channels (12 Single Ended / 4 Differential)	
Common Mode Rejection Ratio, dc to 60 Hz (500 Ω source imbalance)	70 dB	
Common Mode Voltage, dc to 60 Hz	-6 to +5 V peak	
A/D Converter Resolution	16 bits	
Input Range [1]	0 to 5 V, 1 to 5 V, 0.4 to 2 V, 4-20 mA (through 250 Ω)	
Normal Mode Rejection Ratio, at 60 Hz	19 dB	
Normal Mode Filter Response	Single-pole RC, -3 dB @ 6.5 Hz	
Maximum Normal Mode Input (differential inputs, no damage)	± 30 Volts	
Crosstalk, dc to 60 Hz (channel-to-channel)	-60 dB	
Input Impedance (voltage inputs)	> 10 M Ω powered	
Input Scan Rate	50 ms	
Hardware Accuracy (@ CMV = 0 V)	± 0.075% of full-scale (23.5°± 2°C) ± 0.15% of full-scale (0 to 60°C)	
Transmitter Field Power Conditioning	Individually Protected Current Limiting Circuits for Class 1, Div 2 non-incendive interfacing. No fusing required	

Parameter	Specification
Note 1: CC-PAIH01 supports voltage inputs for channels 13-16. CC-PAIH02 supports voltage inputs for channels 1-16 when used with CC-TAIDx1 IOTA. Each channel's 250-Ohm load resistor is connected to the input terminal through a wire jumper on the IOTA. This jumper should be cut by the user on channels to be used with voltage transmitters. For channels 13-16 the low-side input connection is normally connected to system common by a wire jumper on the IOTA. This jumper may be cut by the user to enable differential operation subject to operating within the CMV specification.	

6. Function Matrix

The following tables assist in selecting I/O Modules and IOTAs with similar functional characteristics

AI Function Matrix

Series-C IO			Function							
IOM	NR IOTA	Red IOTA	AI 4-20ma	HART Conf / Status	HART on CTL	HART Fast Ctl	AI 0-5V 1-5V	Int. IS	NR IOTA Size	Differential Inputs
CC-PAIH01 CC-PAIH02	CC-TAIX01	CC-TAIX11	♦	♦	♦	♦	♦		6"	13 - 16
CC-PAIH02	CC-TAID01	CC-TAID11	♦	♦	♦	♦	♦		9"	1 - 16
CC-PAIH01 CC-PAIH02	CC-GAIX21	CC-GAIX11	♦	♦	♦			♦	6"	NA
CC-PAIH51	CC-TAIX51	CC-TAIX61	♦	♦					6"	NA
CC-PAIX01 CC-PAIX02	CC-GAIX21	CC-GAIX11	♦			♦	♦	♦	6"	NA
CC-PAIX01 CC-PAIX02	CC-TAIX01	CC-TAIX11	♦			♦	♦		6"	13 - 16
CC-PAIX02	CC-TAID01	CC-TAID11	♦			♦	♦		9"	1 - 16
CC-PAIN01	CC-TAIN01	CC-TAIN11	♦						6"	None
CC-PUIO31	CC-TUIO31	CC-TUIO41	♦	♦	♦				9”	None

AO Function Matrix

Series-C IO				Function						
IOM	NR IOTA	Red IOTA	AO 4-20ma	HART Conf / Status	HART on CTL	HART Fast CTL	Output Vali-dation	Open Wire Det.	NR IOTA Size	Int IS
CC-PAOH01	CC-TAOX01	CC-TAOX11	♦	♦	♦		♦	♦	6"	
CC-PAOH01	CC-GAOX21	CC-GAOX11	♦	♦	♦		♦	♦	9"	♦
CC-PAOH51	CC-TAOX51	CC-TAOX61	♦	♦				♦	6"	
CC-PAOX01	CC-TAOX01	CC-TAOX11	♦				♦	♦	6"	
CC-PAOX01	CC-GAOX21	CC-GAOX11	♦				♦	♦	9"	♦
CC-PAON01	CC-TAON01	CC-TAON11	♦				♦	♦	6"	
CC-PUIO31	CC-TUIO31	CC-TUIO41	♦	♦	♦	♦	♦	♦	9”	