Foxboro FBM207C P0917GY

Official Technical Reference Excerpt

Foxboro FBM207C P0917GY provides sixteen isolated 48 V dc contact-sense inputs with discrete, ladder-logic, pulse-count and sequence-of-events processing.

VERIFIED PRODUCT ROLE

Characteristic 1

Provides sixteen discrete input channels for its 48 v dc contact sense input module function.

Characteristic 2

Handles 48 V dc dry-contact or solid-state switch states through the documented Foxboro system path.

Characteristic 3

Works with the matching contact-sense termination assembly and redundant module Fieldbus.

Characteristic 4

The module may be installed singly or in a controlled redundant pair.

MANUFACTURER DOCUMENT

Manufacturer source	Schneider Electric, Foxboro Evo FBM207/b/c Voltage Monitor/Contact Sense Input Modules, PSS 31H-2Z7.
Evidence boundary	Technical statements are limited to the identified product or applicable manufacturer family.
Selection control	Use the complete ordering string and verify the installed system before purchase or installation.

APTERPOWER SALES TEAM
WhatsApp / Phone: +86 180 3023 5313
Email: sales13@apterpower.com
Scan the approved WhatsApp code for model-specific support.

Foxboro Evo™ Process Automation System

Product Specifications

Foxboro® by Schneider Electric

PSS 31H-2Z7

FBM207/b/c Voltage Monitor/Contact Sense Input Modules



Discrete inputs can be sensed across all the usual voltage levels found in industrial facilities. The FBM207/b/c uses one of the several termination assemblies to match to the externally powered voltage level. In cases where the inputs are critical to the plant's control scheme, the FBM 207/b/c may be installed as a redundant pair with standard control blocks used to manage the redundancy.

OVERVIEW

The FBM207/b/c Voltage Monitor/Contact Sense Input Module functions as a 16-channel dc voltage monitor or 16-channel contact sensor. Each channel accepts a 2-wire input from a dc voltage source (FBM207) or pair of contacts or solid state switches (FBM207b/ FBM207c). Associated termination assemblies (TAs) support discrete input signals at voltages of 60 V dc, 120 V ac/125 V dc, or 240 V ac. For voltages higher than 60 V dc, the TAs have additional signal conditioning hardware that provides voltage attenuation and optical isolation.

The module is available in three distinct types, and each type with its associated TA supports discrete inputs as shown below:

FBM207	Provides voltage monitoring at: –60 V dc –120 V ac/125 V dc –240 V ac Provides switch inputs with: –External 120 V ac/125 V dc –External 240 V ac
FBM207b	24 V dc Contact Sense
FBM207c	48 V dc Contact Sense

Each discrete input is galvanically isolated from other channels and ground. Group isolated when used with external excitation.

The module performs signal conversion required to interface electrical input signals from field sensors to the redundant module Fieldbus. In addition, it executes programs for Discrete Input, Ladder Logic, Pulse Count, and Sequence of Events, with configurable options of Input Filter Time.

The module can be used as a single unit, or as a redundant pair (two FBM207s). When used as a redundant pair, the modules combine to provide redundancy at the Fieldbus Module (FBM) level, with field input signals received from one common termination assembly though a redundant adapter affixed to the FBMs' baseplate. The input current for redundant modules is doubled. A redundant digital input block in the Foxboro Evo™ Control Software validates each input in conjunction with information to/from the module, and selects the input with the highest quality for processing in the control strategy.

In a redundant configuration, contact sense power from each module is diode OR'd together in the redundant adapter to assure redundant power.

A redundant contact input function block, CINR, is used for each redundant pair of inputs. The CINR block handles input reads and initialization logic for the redundant channels. On each execution cycle of the CINR block, identical reads are sent to both modules, fully exercising the fieldbus and the logic circuitry of each module.

FEATURES

Key features of the FBM207/b/c modules are:

- Sixteen discrete inputs
- Supports discrete input signals at voltages of:
  - 15 to 60 V dc - contact sense
  - 120 V ac/125 V dc - voltage monitoring or switch inputs
  - 240 V ac - voltage monitoring or switch inputs
- Each input is galvanically isolated. Group isolated with external excitation
- Single or redundant modules
- Compact, rugged design suitable for enclosures in Class G3 (harsh) environments
- Executes programs for Discrete Input, Ladder Logic, Pulse Count, and Sequence of Events with configurable Input Filter Time option
- Termination Assemblies (TAs) for locally or remotely connecting field wiring to the FBM207
- Termination Assemblies for per channel internally and/or externally loop powered devices
- Various Termination Assemblies (TAs) have additional signal conditioning hardware that provides voltage attenuation and optical isolation.

COMPACT DESIGN

FBM207/b/c has a compact design, with a rugged extruded aluminum exterior for physical protection of the circuits.

Enclosures specially designed for mounting the FBMs provide various levels of environmental protection, up to harsh environments (Class G3), per ISA Standard S71.04.

VISUAL INDICATORS

Light-emitting diodes (LEDs) incorporated into the front of the module provide visual indication of the Fieldbus Module operational status, as well as the discrete states of the individual input points.

EASY REMOVAL/REPLACEMENT

The module can be removed or replaced without removing field device termination cabling, power, or communication cabling.

When redundant, either module may be replaced without upsetting field input signals to the good module. The module can be removed/replaced without removing field device termination cabling, power, or communications cabling.

SEQUENCE OF EVENTS

The Sequence of Events (SOE) software package (for use with I/A Series® software V8.x and Control Core Services software v9.0 or later) is used for acquisition, storage, display, and reporting of events associated with digital input points in a control system. SOE, using the optional GPS based time synchronization capability, supports data acquisition across control processors at intervals of up to one millisecond, depending on the signal source.

Refer to *Sequence of Events* (PSS 31S-2SOE) to learn more about this package, and to *Time Synchronization Equipment* (PSS 31H-4C2) for a description of the optional time synchronization capability.

I/A Series systems with software earlier than V8.x can support SOE through ECB6 and EVENT blocks. However, these systems do not support GPS time synchronization and use a timestamp sent by the Control Processor which is only accurate to the nearest second and is not synchronized between different Control Processors.

Related models and source control

Use these live ApterPower pages for comparison. Verify each complete ordering string independently.

RELATED PRODUCT REFERENCES

Emerson KJ4001X1-CC1-12P0733X032	Technical-reference companion. Review the complete ordering string before selection.
Emerson CON041-PR6424-000-121	Technical-reference companion. Compare the required interface and system position.
Emerson 1B30035H01	Technical-reference companion. Confirm the execution independently for the intended task.

EXACT-SELECTION CONTROLS

Product identity	Confirm the complete FBM207C P0917GY marking.
System interface	the matching contact-sense termination assembly and redundant module Fieldbus
Technical boundary	Use FBM207C P0917GY only with the matching contact-sense termination assembly and redundant module Fieldbus; verify every interface and the controlled project configuration before energizing or pressurizing the subsystem.
Source	Schneider Electric, Foxboro Evo FBM207/b/c Voltage Monitor/Contact Sense Input Modules, PSS 31H-2Z7.

APTERPOWER SALES TEAM
WhatsApp / Phone: +86 180 3023 5313
Email: sales13@apterpower.com
Scan the approved WhatsApp code for model-specific support.