Siemens 505-4232

01 Map AC groups and address allocation

Draw the four eight-point groups on the terminal schedule and associate each group with its own field source and return. Identify the PLC address used by each interlock. Mark any force or bypass in the maintenance plan before moving the terminal assembly.

If the drawing and controller disagree, resolve the assignment before disconnection; do not rely on the cabinet wire color alone.

Acceptance observation	The physical terminal, group return and input-image address identify the same field device.
Evidence to retain	Connection map and approved baseline
Release boundary	Use the applicable SIMATIC 505 instructions and the approved application acceptance criteria.

02 Isolate independent field sources

Place the controlled equipment in its agreed maintenance state. Isolate the AC field feeds separately from the PLC base supply and verify absence of voltage at the affected terminal groups. Preserve the removable block orientation and label conductors before releasing the assembly.

A powered-down CPU with energized field terminals is an incomplete isolation boundary; locate the independent feed before continuing.

Acceptance observation	All affected external sources are isolated at the point of work.
Evidence to retain	Isolation and supply assessment
Release boundary	Use the applicable SIMATIC 505 instructions and the approved application acceptance criteria.

03 Restore terminal-block orientation

Restore the terminal block to the intended module and slot. Inspect contact seating and each shared return, keeping protective earth separate from the functional return. With wiring access closed and energization authorized, compare terminal voltage against the guaranteed input-state limits under the connected field load.

A borderline state needs a terminal-level voltage and leakage investigation; changing program logic cannot correct an electrically indeterminate input.

Acceptance observation	Each commanded field state produces an unambiguous module input state.
Evidence to retain	Restored interface and configuration
Release boundary	Use the applicable SIMATIC 505 instructions and the approved application acceptance criteria.

04 Exercise point-to-logic transitions

Exercise the permitted contacts individually and follow each transition through the input indication, controller image and application. Hold the stimulus long enough for input conditioning and the controller scan. Observe the final permissive or interlock without defeating unrelated protection functions.

If the module changes but the wrong software point moves, inspect addressing; if no module indication changes, return to the field circuit.

Acceptance observation	The intended point changes and the correct application action follows.
Evidence to retain	Measured response and diagnostic state
Release boundary	Use the applicable SIMATIC 505 instructions and the approved application acceptance criteria.

505-4232

05 Release the interlock chain

Remove temporary stimuli and reconcile all forces and bypasses with the maintenance plan. Confirm normal field states across all four groups, including points not used in the initial test. Save the final terminal-to-address schedule and record any change to the acquisition or interlock design.

An untested group or retained force leaves acceptance incomplete even when the machine can restart.

Technical basis: Siemens SIMATIC 505 Input/Output Modules User Manual, 505-8105-2.

Related product navigation

Siemens 505-4532

Siemens 505-4632

Siemens 505-4732

Related products for separate application assessment; verify the platform and interface. No interchangeability is implied.