ABB CI858K01 3BSE018135R1

COMPLETE PRODUCT INFORMATION / technical and application dashboard

ABB CI858K01 3BSE018135R1 is an AC 800M DriveBus communication interface kit consisting of the CI858 module and TP858 baseplate. It connects an AC 800M controller to ABB drives over the optical DriveBus arrangement.

01 Product identity and operating role

Complete identity
CI858K01 3BSE018135R1

Product function
AC 800M DriveBus Communication Interface Kit

Supply scope
Offer the CI858 communication interface with TP858 baseplate as the complete CI858K01 kit; confirm both markings and any included accessories in the quotation.

System family
AC 800M Communication Interfaces

Engineering priorities

Topology decision
Check each optical path and the NDBU branch arrangement before reconnecting drives.

Kit boundary
Inspect both the CI858 interface and TP858 baseplate against the offered set.

Acceptance record
Verify every configured drive node and controller diagnostic after the change.

System context

The CI858K01 order identity is a kit: CI858 provides the DriveBus communication function and TP858 supplies its mounting baseplate. The interface sits on the AC 800M CEX-Bus and receives power through that controller connection, so the host configuration and baseplate fit are part of a replacement check.

DriveBus is an optical ABB drive network running at 8 Mbit/s. ABB specifies up to 24 drives on one CI858 and up to two CI858 interfaces on one AC 800M controller. When more than one drive is attached, an NDBU branching unit forms the required logical bus with physical star connections; the count alone does not define a valid topology.

The interface supports hot swap but offers neither line nor module redundancy, and ABB does not list it for High Integrity controller use. In rolling-mill or paper-machine sectional-drive systems, restore the approved controller configuration, optical paths and node identities, then prove drive status and diagnostics before handing the line back.

02 Technical capability map

CI858 electrical and network values refer to the interface; kit contents refer to the CI858K01 ordering identity.

Order identity	CI858K01; article 3BSE018135R1
Kit contents	CI858 communication interface plus TP858 baseplate
Controller family	AC 800M
Bus protocol	ABB DriveBus
Communication role	Master interface
Transmission speed	8 Mbit/s
Physical connector	Optical
Drive capacity	Up to 24 ABB drives per CI858
Controller interface capacity	Up to two CI858 modules per AC 800M controller
Branching requirement	NDBU branching unit when more than one drive is connected

Power path	Supplied from controller through CEX-Bus
Typical 24 V consumption	200 mA
Hot swap	Supported
Line redundancy	Not provided
Module redundancy	Not provided
High Integrity controller use	Not supported
Operating temperature	0 to +55 °C
Storage temperature	-40 to +70 °C
Enclosure protection	IP20
Corrosion class	G3 to ISA 71.04

03 Integration and use

Sectional drive coordination

Connect AC 800M control to multiple ABB drives using an approved DriveBus topology.

Rolling-mill drive systems

Carry drive communication in the controller arrangement designed for sectional mill operation.

Paper-machine control

Support drive-group communication where the installed machine uses AC 800M DriveBus.

Maintenance replacement

Replace the CI858/TP858 kit while retaining the configured controller and optical network identity.

Technical decisions

Kit versus module	CI858K01 names the module and TP858 baseplate together; verify both when receiving the unit.
Host power path	The interface obtains operating power from the AC 800M CEX-Bus, so host fit must be checked.
Optical network	Inspect clean optical terminations and the documented route before deciding a board has failed.
Multi-drive topology	An NDBU branch arrangement is required for more than one drive; retain the logical bus map.
Capacity planning	Check both the drives-per-interface count and the interfaces-per-controller limit.

Hot-swap boundary	Supported hot swap does not remove the need for process isolation and a site change procedure.
Resilience review	No module or line redundancy is specified for this interface.
Host restriction	Do not infer use in a High Integrity controller from generic AC 800M compatibility.
Acceptance evidence	Record module/baseplate identities, branch paths and node diagnostics after installation.

04 Installation and diagnostic review

Kit identity
Verify the CI858 module and TP858 baseplate are both present in the offered CI858K01 kit.

CEX-Bus isolation
Follow the controller maintenance procedure before handling the module or baseplate.

Optical inspection
Keep optical contacts clean and match each drive link to the approved topology.

Branching unit
Check the NDBU arrangement when more than one drive is connected.

Controller limits
Confirm the installed CEX-Bus allocation and approved AC 800M configuration.

Functional proof
Check every configured drive node, diagnostics and restart behavior before release.

Technical FAQ

How should the NDBU branch path be proved after replacing CI858K01 3BSE018135R1?	Compare the documented physical star with the configured logical DriveBus sequence, then check every drive node in AC 800M diagnostics. Verify one optical path at a time so a swapped branch is not hidden by a successful link at another node.
What does hot swap mean for CI858K01 3BSE018135R1 during maintenance?	The interface is designed for hot swap, but the controller and process must still follow the approved maintenance procedure. Record drive states, isolate the affected control function as required and verify every node after insertion.
How can an optical DriveBus fault on CI858K01 3BSE018135R1 be isolated?	Inspect the optical connectors and NDBU branch paths, then compare controller diagnostics with drive-node status. Test one documented path at a time under site procedure rather than changing several links blindly.
Why is CI858K01 3BSE018135R1 not a redundant communication path by itself?	ABB specifies neither line nor module redundancy for CI858. Review the process response to loss of this interface and the available maintenance bypass before a live replacement.
What should be matched before replacing a CI858K01 3BSE018135R1 kit?	Compare the CI858 and TP858 markings, controller slot and software configuration, drive-node assignment and optical connector layout with the installed assembly. Confirm both kit elements are included in the offer.
What can cause a drive to remain offline after CI858K01 3BSE018135R1 is fitted?	A wrong optical branch, missing NDBU path, changed controller configuration or a drive-node mismatch can prevent communication. Use AC 800M diagnostics and the approved bus map to locate the affected path.

05 Service and acceptance

Module swap
Record process state and follow the approved hot-swap procedure; confirm node recovery afterwards.

Power concern
Check the CEX-Bus host and interface status rather than adding an external supply.

Capacity concern
Count configured drives and CI858 modules against the documented controller arrangement.

HI controller concern
Stop selection if the host is a High Integrity variant; confirm an approved alternative.

Loss of communication
Treat the interface as a nonredundant path and apply the machine contingency procedure.

As-left record
Save module/baseplate markings, branch map, drive diagnostics and restart test.

Lifecycle and supply boundary

A current ABB lifecycle phase for the complete CI858K01 3BSE018135R1 order identity has not been established. Request replacement and support guidance for the installed controller configuration.

Evidence and applicability

ABB AC 800M Communication Interfaces data sheet, 23 September 2026; CI858 product data. CI858 electrical and network values refer to the interface; kit contents refer to the CI858K01 ordering identity.

Additional installation context: ABB System 800xA 7.0 Product Catalog, CI858K01 package identity.

Related product references

Catalog navigation only; these items are not identified as substitutes.

ABB RLM02 3BSE091723R1	Other product reference; confirm the complete installed model.
ABB TU835V1 3BSE013236R1	Other product reference; confirm the complete installed model.
ABB 3BHE021887R0101 UBC717 BE101	Other product reference; confirm the complete installed model.

Discuss the complete marking with Apter Power.
sales13@apterpower.com | +86 18030235313